

# SAINT2 Version 1.2 CABLE (REV A)

## Pinout and wire color

<b>PIN#</b>	<b>CONDUCTOR COLOR</b>	<b>SIGNAL</b>
<b>1</b>	Green w/ Black Stripe	SWCAN1
<b>2</b>	Brown	FT 2_H
<b>3</b>	Red	VBATT
<b>4</b>	Orange	TRIGIN
<b>5</b>	Yellow	SWCAN2
<b>6</b>	Green	DB4
<b>7</b>	Blue	KEYWORD
<b>8</b>	Purple	CAN_1_H
<b>9</b>	Gray	CAN_1_L
<b>10</b>	White	CAN_2_H
<b>11</b>	Peach	CAN_2_L
<b>12</b>	Light Green	BArT_SW
<b>13</b>	Black w/ White Stripe	FT_2_L
<b>14</b>	Brown w/ White Stripe	CLASS2
<b>15</b>	Red w/ White Stripe	IIC_CLK
<b>16</b>	Orange w/ White Stripe	FT 1_H
<b>17</b>	Green w/ White Stripe	FT_1_L
<b>18</b>	not connected	DB1
<b>19</b>	not connected	DB2
<b>20</b>	not connected	DB3
<b>21</b>	not connected	IIC_DATA
<b>22</b>	Yellow w/ Black Stripe	TRIGIN2
<b>23</b>	Black	GND
<b>24</b>	Gray w/ Black Stripe	TRIGOUT
<b>25</b>	Peach w/ Black Stripe	TRIGOUT2